LG InfoComm U.S.A., INC.

TM-510
Tri-Mode CDMA Phone

Programming Instruction Guide

All steps must be completed

PREPARATION

STEP	ACTION
1	Press MENU 3, 0 to access Programming Menu
2	Enter Service Programming Code (default 000000)
3	Press 1 for Service Programming (Prog. Mode)

PROGRAMMING STEPS

	Item	Default	Action
1	ESN	201xxxxxxxx	Enter [ok] (Display Only)
2	NAM 1 Phone Number	000-000-0000	Enter NAM 1 Phone Number [ok]
3	NAM 1 Home SID	0	Enter Home System I.D. [ok]
4	NAM 1 Name	NAM1	Enter NAM 1 Name [ok]
5	**Basic NAM 1 Programming is Complete**	**[Exit] [More]**	**Enter [Exit] to complete Short Programming, Enter [MORE] to advance to Extended Programming**
6	Service Programming Code	000000	Enter Service Sec. Code [ok]
7	NAM 1 Mobile Country Code	000	Enter Mobile Country Code [ok]
8	NAM 1 NMSID	000000000000	Enter 00 + the Phone Number (auto-set from step 2) [ok]
9	NAM 1 PRL Enabled?	Yes or No	Enter [ok] (Display Only)
10	NAM 1 CDMA Directory #	0000000000	Enter CDMA Directory # (auto-set from step 2) [ok]
11	NAM 1 CDMA Home SID/NID 01	0/65535	Select [edit] to enter SID/NID values [ok]
12	**Press "UP" arrow to access SID/ NID pairs (upto 20 pairs), choose [edit] to access, [ok] to store**		
13	NAM 1 CDMA Primary CH A	283	Enter NAM 1 CDMA Primary CH A (preset)
14	NAM 1 CDMA Second CH A	691	Enter NAM 1 CDMA Second CH A (preset)
15	NAM 1 CDMA Primary CH B	384	Enter NAM 1 CDMA Primary CH B (preset)
16	NAM 1 CDMA Second CH B	777	Enter NAM 1 CDMA Second CH B (preset)
17	NAM 1 Lock-Out SID/NID 01	0/0	Select [edit] to enter Lock-Out SID/NID values [ok]
18	**Press "UP" arrow to access SID/ NID pairs (upto 10 pairs), choose [edit] to access, [ok] to store**		
19	NAM 1 CDMA Home Sys Reg	Yes or No	Enter Yes or No to enable/disable Home System Registration [ok]
20	NAM 1 CDMA Forn SID Reg	Yes or No	Enter Yes or No to enable/disable Foreign System ID Registration [ok]
21	NAM 1 CDMA Forn NID Reg	Yes or No	Enter Yes or No to enable/disable Foreign Network ID Registration [ok]
22	NAM 1 AMPS Phone Number	0000000000	Enter AMPS Phone Number (auto-set from step 2) [ok]
23	NAM 1 AMPS Home SID	0	Enter AMPS System (auto-set from step 2) [ok]
24	NAM 1AMPS 1st Page CH	334	Enter AMPS Paging Channel (auto-set from step 3) [ok]
25	NAM 1 AMPS Auto-Reg	Yes or No	Enter Yes or No to enable/disable Autonomous Registration [ok]
26	NAM 1 Access Overld Class	0	Enter [ok] (Display Only, auto-set from step 2)
27	**NAM 2 Settings - Select [edit] to access NAM 2 (repeat steps 2 ~ 26 above)**		
28	Phone Model	61	Enter [ok] (Display Only)
29	Slot Cycle Index	1	Enter Slot Cycle Index [ok]
30	Exit Service Programming		Programming Complete